
BOS 08E-PS-KD20-S49 Ordercode: BOS01NN





1) Optical axis 2) Output function





Electrical connection

Connection M8x1-Male, 3-pole
Contact, surface protection Gold plated
Protection against device mix-ups yes
Short-circuit protection yes

Electrical data

Load capacitance max. at Ue 0.5 µF No-load current lo max. at Ue 15 mA Operating voltage Ub 10...30 VDC Polarity reversal protected ves Rated insulation voltage Ui 75 V DC Rated operating current le 100 mA Rated operating voltage Ue DC 24 V Ready delay tv max. 20 ms Ripple max. (% of Ue) 10 % Switching frequency 500 Hz Turn-off delay toff max. 1 ms Turn-on delay ton max. 1 ms Utilization category DC-13 Voltage drop Ud max. at le 0.7 V

Environmental conditions

Ambient temperature -5...55 °C
IP rating per IEC 60529 IP67

General data

Approval/Conformity cULus CE
Basic standard IEC 60947-5-2

Internet www.balluff.com
Balluff Germany +49 (0) 7158 173-0, 173-370
Balluff USA 1-800-543-8390
Balluff China +86 (0) 21-50 644131

Series 08E
Style Cylinder
Straight optics

Material

Housing material Stainless steel Material sensing surface PMMA

Mechanical data

Dimension Ø 8 x 40 mm Fastening detail Nut M8x1

Optical data

Beam characteristic Divergent

LED group per IEC 62471 Exempt Group

Light spot size Ø 3.0 mm Light exit

Light type LED Red light

Principle of optical operation Diffuse sensor, energetic

Wave length 645 nm

Output/Interface

Switching output PNP Normally open (NO)

Range/Distance

Measuring range1...60 mmRange1...60 mmRated operating distance Sn60 mm

Photoelectric Sensors

BOS 08E-PS-KD20-S49 Ordercode: BOS01NN



Remarks

Order accessories separately. For additional information, refer to users guide. Only for applications per NFPA 79 (machines with a supply voltage of maximum 600 V). Use an R/C (CYJV2) cable with suitable properties for

attaching the device.


Actuation object (target): gray card, 200 x 200, 90 % remission, lateral approach, approach direction vertical to lens axis plane.

The sensor is functional again after the overload has been eliminated.

Connector view



Wiring Diagram



Symbols for Optoelectronic Sensors

