





 ϵ







Model Number

RLK31-54/25/31/115 SET

Retroreflective sensor


Features

- Photoelectric sensor for detecting people, objects and vehicles
- · Large construction with small housing
- Not sensitive to ambient light
- Version for universal voltages
- Relay output
- Version with accessories in scope of delivery

Product information


Series 31 is a range of cost-effective and, most importantly, reliable photoelectric sensors for standard applications in the fields of material handling and logistics, and for monitoring industrial doors, elevators, and automatic gates. The ultrasonic-welded plastic housing provides a high degree of protection, making these sensors ideal for tasks in harsh outdoor conditions. These sensors are currently the most compact "wide range power supply sensors" that can work with any DC and AC voltage between 24 V and 240 V. In addition to the robust technology, the sensors offer numerous product details that help the user with assembly, connection and operation.

Dimensions




Diffusive mode sensor Thru-beam sensor Diffusive mode sensor with background suppression red

Electrical connection



Indicators/operating means





| | 1 | Operating display | green |
|--|---|-------------------|--------|
| | 2 | Signal display | yellow |
| | 3 | Emitter | |
| | 4 | Receiver | |



Technical data General specifications Effective detection range

0 ... 9000 mm 20 ... 9000 mm Reflector distance Threshold detection range 12 m reflector C110-2 Reference target Light source LFD

Light type modulated visible red light, 630 nm Diameter of the light spot approx. 200 mm at a distance of 6 m 3

Angle of divergence Ambient light limit 50000 Lux reflector C110-2 Accessories provided

OMH-RL31-01 mounting bracket with mounting materials

Functional safety related parameters

790 a Mission Time (T_M) 20 a Diagnostic Coverage (DC) 0 %

Indicators/operating means

Operation indicator LED green: power on

Function indicator LED yellow:

1. LED lit constantly: signal > 2 x switching point (function

2. LED flashes: signal between 1 x switching point and 2 x swit-

china point

3. LED off: signal < switching point

Electrical specifications

24 ... 240 V AC Operating voltage U_{B} 12 ... 240 V DC No-load supply current < 40 mA I_0 Power consumption P_0 \leq 2 VA

Output

Switching type light on Signal output Relay, 1 alternator Switching voltage max. 240 V AC Switching current

DC: max. 150 W AC: max. 750 VA Switching power

Switching frequency 20 Hz Response time ≤ 25 ms

Ambient conditions

Ambient temperature -25 ... 55 °C (-13 ... 131 °F) Storage temperature -40 ... 70 °C (-40 ... 158 °F)

Mechanical specifications

Degree of protection Connection 2 m fixed cable

Material

Housing Polycarbonate Optical face РММА Mass 154 g

Compliance with standards and directi-

ves

EMC Directive 2004/108/EC Directive conformity Standard conformity

EN 60947-5-2:2007 IEC 60947-5-2:2007 Product standard

Standards EN 62103

Approvals and certificates

EAC conformity TR CU 020/2011 TR CU 004/2011

II , rated voltage ≤ 250 V AC with pollution degree 1-2 accor-Protection class ding to IEC 60664-1 Output circuit basis insulation of input circuit according to EN 50178, rated insulation voltage 240 V AC

CCC approval Certified by China Compulsory Certification (CCC)

Typical applications

- Monitoring closing edges of automatic industrial doors and elevators
- Monitoring the swing range of automatic
- Detecting and tracking objects in material handling

Detection area



Accessories

REF-H50

Reflector, rectangular 51 mm x 61 mm, mounting holes, fixing strap

REF-H60-2

Reflector with mounting holes

RFF-H85-2

Reflector, rectangular 84.5 mm x 84.5 mm, mounting holes

REF-H160

Reflector, rectangular 60 mm x 18 mm, mounting holes

REF-H180

Reflector, rectangular 180 mm x 40 mm, mounting holes

REF-C110-2

Reflector, round ø 84 mm, central mounting hole

OFR-100/100

Reflective tape 100 mm x 100 mm

Reflector Weather Cap

Weather hood for series reflector

Other suitable accessories can be found at www.pepperl-fuchs.com



Curves/Diagrams

